

Additional manual for LA-90 Set

Contents of package

Please check if the following items are included:

- «LA-90»
- 1 rechargeable battery
- 1 power supply unit
- 1 black inlay strip
- 4 rubber feet
- 1 microphone base
- 1 microphone neck
- 1 XLR-cable to 3,5 mm jack
- 1 handset
- 1 spiral lead RJ to 3,5 mm jack
- 1 manual LA-90 + additional manual LA-90 Set
- 1 warranty card

In case of missing components, please contact your dealer or manufacturer.

Setup

Insert battery

(Please refer to page 9 of the manual)

1. Tabletop microphone:



Insert the microphone neck into the socket of the microphone base. Push it in until the latch locks the connection. Connect the XLR cable with the socket on the rear side of the microphone base.

2. Handset

Plug the transparent RJ-connector of the spiral cable into the socket of the handset. The handset can be hooked onto the protrusion of the black inlay strip.

3. Connecting the microphone and handset to the LA-90

Plug the 3,5 mm jack of the microphone into the microphone port of the LA-90. **Important:** Set the microphone selector switch to the lower position. Otherwise there is a risk of feedback (loud whistling noises)! Connect the handset cable's 3,5 mm jack with the earphone socket of the LA-90.

4. Power supply

Connect the power supply unit with the power-in socket of the LA-90. Plug the power supply unit into an electric mains socket.

Operation


Press the «I»-button to switch the device on. To switch the device off, press «O».
Adjust the microphone sensitivity with the control dial button located above the microphone connector.
Adjust the handset volume with the control dial button above the head-phone connector.

Note: When switched on, the green light on the back and the blue light on the front of the LA-90 will be lit. The microphone and handset are ready to use.



LA-90 with black inlay strip

Tabletop microphone



Handset

Spiral cable RJ / 3,5 mm jack



XLR-cable / 3,5 mm jack

